

marantz



SR8015

Marantz SR8015 11.2ch 8K AV amplifier with 3D Audio, HEOS Built-in and Voice Control

Marantz has long set the standard for AV amplifiers combining home theatre prowess with the most musical sound, and the SR8015 takes that capability to unprecedented levels. Experience the staggering impact of audio quality, which is quite simply an intoxicating mix of effortless power, amazing detail and sensational depth. This flagship AV amplifier marks the pinnacle in Marantz build quality with a centrally mounted toroidal transformer, copper plating and a symmetrical monolithic design.

- Premium-performance 11-channel amplifier: Delivering a masterful 205W per channel so you experience your entertainment in remarkable detail.
- 8K/60Hz and 4K/120Hz pass-through support for every entertainment need: With the latest technology in HDMI support, enjoy 8K quality video from your 8K source devices or with 8K upscaling from Full HD or 4K sources.
- Featuring the most advanced three-dimensional audio formats: Dolby Atmos, Dolby Atmos Height Virtualization Technology, DTS:X and DTS Virtual:X, IMAX Enhanced and Auro-3D processing are all supported to allow you to listen to all of your favourite audio styles.
- DTS:X Pro support: DTS:X Pro is capable of processing up to 13 channels, wowing listeners with the most cutting edge DTS technology (available in a future firmware update).
- Enhanced Audio Return Channel (eARC) HDMI support: Through the main HDMI output, connect your TV with eARC HDMI support to allow uncompressed and object-based audio formats like Dolby Atmos and DTS:X directly from a smart TV app to your AV amplifier.
- The greatest technology for home cinema: Support for the latest HDR formats including HDR10, HDR10+, HLG, Dolby Vision, 4:4:4 colour resolution and BT.2020, as well as Dynamic HDR provides exceptional picture quality for brightness, clarity and contrast.
- Advanced gaming specifications: With 4K/120Hz pass-through, Variable Refresh Rate (VRR), Auto Low Latency Mode (ALLM) and Quick Frame Transport (QFT), experience gaming thrills with amazing imaging and reduced lag.
- High-resolution streaming for audiophile approved sound: Play back ALAC, FLAC and WAV lossless files up to 24-bit/192-kHz as well as DSD 2.8MHz and 5.6MHz tracks, and enjoy your music exactly as the artist intended.
- Exclusive components elevate the Marantz sonic signature: Marantz proprietary HDAM circuit boards, Current Feedback circuitry, AKM AK4458 32-bit D/A converters, and Hybrid PLL Clock Jitter Reducer produce more detailed, dynamic sound.
- Almost unlimited music sources: Stream from music services like Spotify Free and Premium, Amazon Music HD, Tidal and more, or stream directly from smart devices via AirPlay 2 or Bluetooth
- Features HEOS Built-in and the free HEOS App: Your key to digital music streaming, multi-room audio and voice control throughout your entire home.

Modern Musical Luxury



SR8015

Technical Specs



Multichannel surround		
DTS HD Master / DTS:X / DTS:X Pro	•/•/•	
DTS Neo:X / DTS Neural:X	-/•	
DTS VirtualX	•	
IMAX Enhanced	•	
Dolby TrueHD / Dolby Atmos / Dolby Atmos Height Virtualization	•/•/•	
Dolby ProLogic IIz / Dolby Surround	-/•	
Front Wide Speakers	Dolby / DTS	
Auro 3D	•	
MPEG-H	• (Firmware Update)	
Multichannel Stereo	•	
Max Number of Processing (Preamp) Channels	13.2	
Sound Enhancements		
Discrete Power Amplifier	11	
Copper Plated Chassis	•	
Power Transformer: Toroidal / EI	Toroidal	
Current Feedback Topology	•	
Hyper Dynamic Amplifier Modules (HDAM)	•	
Pure Direct	•	
Gold Plated RCA Terminals	•	
Clock Jitter Reducer	•	
Audyssey	MultEQ XT32	
Audyssey Dynamic EQ / Dynamic Volume	•/•	
Audyssey LFC	•	
Compressed Audio Enhancer: MDAX2	•	
Network		
HEOS Multi-room and Streaming	•	
Bluetooth Re-transmit for Bluetooth headphones	•	
Amazon Alexa / Google Voice Assistant / Apple HomePod	•/•/•	
Lossy Formats: MP3 / WMA / AAC	•/•/•	
Lossless Formats: FLAC HD 192/24 / WAV 192/24 / ALAC 192/24	•/•/•	
DSD Audio Streaming	• (2.8/5.6MHz)	
FLAC HD 192/24	•	
Gapless Playback	• (FLAC, WAV, ALAC, DSD)	
AirPlay Audio Streaming	• (AirPlay2)	
Internet Radio	• (TuneIn)	
Spotify	• (connect)	
Amazon Music HD / Deezer / TIDAL / Napster / others	•/•/•/• / varies per region	
Compatible with Remote APP for Smart Phones	Android / iOS	
Compatible with Remote APP for Tablets	Android / iOS / Amazon Kindle	
Ethernet Port	•	
Wi-Fi	•	
Bluetooth	•	
HDMI		
HDMI Inputs: Back / Front	7 / 1	
HDCP2.3 support	•	
HDMI Outputs: Main / Zone	2 / 1	
Video Conversion Analogue -> HDMI	•	
HDMI to HDMI scaling	up to 8K 60/50Hz	
8K/60Hz / 4K/120Hz / CEC / eARC	•/•/•/•	
Dolby Vision / HDR10+ / Dynamic HDR / HLG	•/•/•/•	
ALLM (Auto Low Latency Mode) Pass-through for gaming	•	
Variable Refresh Rate / Quick Frame Transport / Quick Media Switching	•/•/•	
HDMI pass-through in Standby Mode	•	
DSD Audio Capability	•	
Auto LipSync	•	
Multiroom / CI		
HEOS Multi-Room Integrated	•	
TV Sound Grouping	•	
Multiroom zones	3	
Zone Audio Source: HDMI / Opt, Coax / Network, USB / Analogue	• (2ch) / • (2ch) / •/•	
Zone Audio Output: Speaker / Preout	•/•	
Zone HDMI Output from HDMI Source	•	
IP Control / RS232 Control / Web Control / App Control	•/•/•/•	
IR Flasher In	•	
Marantz Remote Bus	•	
DC Trigger Output	2	
HDMI Diagnostics	•	

Others		
Auto Speaker Setup by Microphone		Audyssey MultEQ XT32
FL Display		2-lines + Port Hole
Graphic User Interface - GUI		Advanced
ISF Certification		•
GUI Languages		9
Setup Assistant		•
Smart Select		•
Firmware Update by Network / USB		•/•
Variable Cross Over		•
Optimized Bass Redirection		•
Bass Sync		•
ECO Mode		•
Auto Power Off		•
Sleep Timer		•
Video Inputs/Outputs		
Composite In / Out		4+1 / 2
Component In / Out		3 / 1
HDMI In / Out		7+1 / 3
Multi-Room Video Out: Video / HDMI		•/•
Audio Inputs/Outputs		
Analogue In / Out		7+1 / -
Phono (MM) In		•
Digital In: Optical / Coaxial		2 / 2
Multi-Room Out: Analogue / Digital		2 / -
Multichannel Pre Out		• (13.2)
Subwoofer Out		2
7.1 Multichannel Input		•
Other		
Speaker Terminal: Gold Plated Screw / Regular Screw		• / -
Number of Speaker Terminals		13
Speaker A / B		assignable
Bi-Amp Drive		assignable
Multi-Room Speaker Terminal		assignable
Front Inputs: Audio / Composite / Digital (Opt) / HDMI / USB		•/•/•/•/•/•
USB Audio		•
FM/AM Tuner		-
General Power		
Number of Poweramps		11
Power Output (8 ohm, 20 Hz - 20 kHz, 0.05% 2ch Drive)		140 W
Power Output (6 ohm, 1 kHz, 0.7% 2ch Drive)		175 W
Power Output (6 ohm, 1 kHz, 1% 1ch Drive)		205 W
70% Guarantee		•
General		
Metal Front Panel		•
System Remote Control		RC045SR
Pre-Programmed / Learnable / LCD Display		•/•/•
Power Consumption in W		780 W
Power Consumption No-Sound (ECO on / off) in W		65 W / 110 W
Standby Consumption in W		0.2
CEC Standby Consumption in W		0.5
Network Standby Consumption in W		3.7
Maximum Dimensions in mm		
Antenna:Horizontal:(W x D x H)		440 x 460 x 185
Antenna:Vertical:(W x D x H)		440 x 460 x 248
w/o Antenna:(W x D x H)		440 x 450 x 185
Weight in kg		
Carton Maximum Dimensions (W x D x H) in mm		541 x 537 x 304
Carton Weight (incl. product) in kg		20.9
SAP Code / EAN Black		SR8015/N1B 4951035072790
SAP Code / EAN Silver-Gold		SR8015/N1SG 4951035072806

Design and specifications are subject to change by Marantz without notice.

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. Dolby, Dolby Atmos, and the double-D symbol are trademarks of Dolby Laboratories. DTS, the Symbol, DTS in combination with the Symbol, DTS:X, and the DTS:X logo are registered trademarks or trademarks of DTS, Inc. in the United States and/or other countries. The Spotify software is subject to third party licenses found here: www.spotify.com/connect/third-party-licenses. Other trademarks and trade names are those of their respective owners. Marantz is a trademark or registered trademark of D&M Holdings, Inc.

www.marantz.com

Sound United
A Division of D&M Europe B.V.
P.O. Box 8744
5605 LS Eindhoven
The Netherlands